Panasonic Choke Coils

### Power Choke Coil

Series: PCC-D124H (NX1)

Low profile, High power, Low loss





#### ■ Features

- High power, high inductance (No saturation performance limitation due to metal dust core)
   (17 A to 32 A/1.25 μH to 0.32 μH)
- Low loss due to low R<sub>DC</sub> (using flat wire)
- Low buzz noise due to its gap-less structure
- Surface mount, low profile
   (H) 3.9 mm×(L)13.0 mm×(W)12.9 mm
- RoHS compliant

## ■ Recommended Applications

- DC-DC converter for CPU in PCs
- Thin on-board power supply modules for servers

## ■ Standard Packing Quantity

• 500 pcs./Reel

### ■ Explanation of Part Numbers

1	2	3	4	5	6	7	8	9	10	11	12
E	Т	Q	Р		Н				В		
Product Code			Classification Size		Winding	Inductance		Core	Packaging	Suffix	

## ■ Standard Parts

Dort No.		L1		L2 (Ret	ference)	Rated	DC resistance (at 20 °C) (mΩ) max.
Part No.	(µH)	Tolerance (%)	Measurement current (A)	(µH)	Measurement current (A)	current (A)* <sup>2</sup>	
ETQP3H0R4BFA	0.36		23	0.32	32	23	1.04
ETQP3H0R8BFA	0.80	±20	16	0.71	22	16	2.33
ETQP3H1R4BFA	1.43		12	1.25	17	12	4.52

<sup>(\*1)</sup> Inductance is measured at 100 kHz.


<sup>(\*2)</sup> Rated current defines actual value of DC current, when temperature rise of coil becomes 40 K.

# ■ Performance Characteristics (Reference)


## Inductance vs DC Current

# 


# Case temperature vs DC Current



### ■ Dimensions in mm (not to scale)





 $\square$ 



### ■ Connection

## ■ Recommended Land Pattern in mm (not to scale)





01 Oct. 2012

■ Packaging Methods, Soldering Conditions and Safety Precautions (Power Choke Coils for Consumer use)
Please see Data Files