




SMA CONNECTORS



Active

PRODUCT DRAWING
English

TE CONNECTIVITY (TE) PLUG,RT ANGLE,SMA

AMP | SAM , SMA

228626-1
TE Internal Number: 228626-1
Mil-Spec: M39012/80-3308

Always EU RoHS/ELV Compliant

Applies To **Coaxial Cable**

Panel Mount **Without**

Body Material **Stainless Steel**

Body Plating Finish **Passivated**

50 Ohm **Yes**

Product Drawings

[CONNECTOR, COAXIAL, RF, PLUG, RIGHT ANGLE, MIL F, SERIES SMA](#)

PDF (TIFF AVAILABLE)
English

[CONNECTOR, COAXIAL, RF, PLUG, RIGHT ANGLE, MIL F, SERIES SMA](#)

PDF (TIFF AVAILABLE)
English

Instruction Sheets

Instruction Sheet (U.S.)

[SERIES SMA RIGHT ANGLE PLUG PASSIVATED BODY F/RG-402/U CABLE P/N 228626-1](#)

PDF
English

Please review product documents or [contact us](#) for the latest agency approval information. Please Note: Use the Product Drawing for all design activity.

Product Type Features

Applies To	Coaxial Cable
RF Connector Type	SMA
Connector Style	Plug
Cable Type	RG 402 Semi-Rigid
Product Type	Connector - RF
Shrink Tubing	Without
Retractable Collar	Without
Dielectric Material	PTFE
Grade	Military

Configuration Features	Snap-Lock	Without
Electrical Characteristics	50 Ohm	Yes
	75 Ohm	No
	Impedance (Ω)	50
Signal Characteristics	Frequency (GHz)	18
Body Features	Body Material	Stainless Steel
	Body Plating Finish	Passivated
	Body Style	Right Angle
	Ferrule Material	Brass
	Interface Seal Material	Silicone Rubber
	Ferrule Plating Material	Nickel
Contact Features	Captivation Method	Mechanical
	Center Contact Plating Material	Gold
	Center Contact Material	Beryllium Copper
	Captivated Contacts	With
	Center Contact	With
Termination Features	Cable Termination Type	Crimp
	Crimp Type	Hex
Mechanical Attachment	Panel Mount	Without
	Coupling Nut Plating Finish	Passivated
	Safety Wire Holes	Without
	Polarized	No
	Coupling Nut Material	Stainless Steel
Dimensions	Height	.554 in
	Length	17.02 mm [.67 in]
Industry Standards	Military Category	F
Packaging Features	Packaging Method	Package

Other

Comment

**Die Set not included with Pneumatic Tool:
Must be purchased separately., Locator not
included in Hand Tool Kit: Must be
purchased separately.**

Product Compliance

[Statement of Compliance](#)
PDF

[VIEW ALL PRODUCT COMPLIANCE](#)