

Soft Shell Connectors

.163" Centerline, 600 V, 9.5 A max. (Mini Universal MATE-N-LOK)

AMP 794219-1 Active [Active](#)

RoHS Compliant [RoHS Compliant](#)

(Tyco Electronics P/N: 794219-1)

[CAD Geometry](#) | [Search for Parts](#)

Document links for this part cannot be displayed. Your browser does not support inline frames or is currently configured not to display inline frames. Inline frames are supported in both Internet Explorer 5 and Netscape 6, as well as all later versions of these browsers.

Related Part Information		
General Information	eCommerce	Related Part Information
<input type="checkbox"/> General Info <input type="checkbox"/> Sales Info <input type="checkbox"/> Assembly Subcontractors	<input type="checkbox"/> Pricing <input type="checkbox"/> Product Availability	<input type="checkbox"/> Tooling

Searchable Features:

Brand:	AMP
RoHS/ELV Compliance:	RoHS compliant, ELV compliant
Lead Free Solder Process:	Not relevant for lead free process
Product Type:	Contact
Connector Line:	Mini-Universal MATE-N-LOK 2
Gender:	Socket
Packaging Method:	Strip
Wire Range (mm [AWG]):	0.12-0.35 ² [26-22]
Contact Material:	Brass
Wire Insulation Diameter (mm [in]):	1.20 – 1.75 [0.047 – 0.069]

Other Properties:

RoHS/ELV Compliance History:	Always was compliant
Contact Diameter (mm [in]):	0.99 [0.039]
Stock Thickness (mm [in]):	0.25 [0.010]
Voltage (VAC):	600
Current Rating (Amps.):	9.5

**Contact Termination
Area Plating:**

Pre-Tin

Comment:

HDM Applicator part number ending in -3 is used on AMPOMATOR CLS Machine with T or G Terminators, -4 is used on AMP-O-ELECTRIC Model K Machine, -5 is used on AMP-O-ELECTRIC Model G Machines. These contacts can be used in either Mini-Universal MATE-N-LOK 2 Plug or Cap housings ONLY.

[Copyright](#) and [Privacy Statement](#)

Visit [Tyco International, Ltd.](#)

[Products](#) | [Catalog](#) | [Brands](#) | [Industries](#) | [Commerce](#) | [Supplier](#) | [Contact Us](#) | [About](#) | [Home](#)

i2 Technologies US, Inc.

HTML Pages converted to PDF Document

This document contain component information from the manufacturer's website which are not available in a revision controlled document from the manufacturer. To facilitate the addition of these parts into the Electronics Database, we are converting the HTML pages related to that part, from the manufacturer's website into Adobe PDF format. The contents of this document is based on the information provided on the manufacturer's website, therefore the information may have been changed by the manufacturer since this was created.

